

DHT-588BA

Home Theater System

DENON

5.1 Home Theater System featuring AVR-588 HDMI1.3 receiver and Boston Acoustics Horizon MCS 130 speaker system.



Bullet points

AVR-588 Receiver Features

The Latest HD Video Support

- HDMI1.3a switching*
- Deep Color up to 36-bit and xvYCC broader color space support
- Discrete devices for ultimate HD video performance in each block
- 1080p video pass through

*No audio support

Denon Design Solutions for Maximizing Content Quality

- Identical quality and power for all 7 channels, 75W x 7ch
- Discrete devices for ultimate performance in each block
- New 32-bit floating point DSP
- Minimum signal path design
- Direct Mechanical Ground for stable drive
- Dual power transformer
- Denon customised block capacitor
- Separate unit design

Digital Media Connectivity

- Network Audio/Photo Ready (optional ASD-3N/3W)
- iPod Audio/Photo and Video playback (optional ASD-1R/3N/3W)
- XM Ready

*Shown ASD-3W



Compressed Audio Restorer

Denon's new audio technology for MP3/WMA/AAC compressed audio formats to reproduce higher frequency range and deeper bass sound.

Ease-of-Use

- 3 Quick Select Buttons
- New back panel layout

Boston Acoustics MCS 130 Features

Two way design front and center speakers

- Dual 3 1/2" mid-bass drivers and 1" soft dome tweeter
- Reduced Baffle Diffraction Design for wider, smoother dispersion
- MagnaGuard video shielding
- Adjustable footings
- 5-way gold-plated binding posts
- Built-in wall mount brackets
- Changeable grilles to match your environment (optional)

Two way design surround speaker

- 3 1/2" mid-bass driver
- 1" soft dome tweeter
- Reduced Baffle Diffraction Design for wider, smoother dispersion
- MagnaGuard video shielding
- Adjustable footings
- 5-way gold-plated binding posts
- Built-in wall mount brackets
- Changeable grilles to match your environment (optional)

Matching Subwoofer

- 10" down-firing design
- 200 watt power amplifier
- Deep Channel Design (DCD) for more bass from less amplifier power

Receiver AVR-588 Input / Output terminals

IN			OUT		
	HDMI	2		HDMI Monitor	1
	Component	3		Component Monitor	1
	S-Video	3		S-Video REC	1
	Composite	4		Monitor	1
	Analog audio (Tuner included)	8		Composite REC	1
	Analog EXT. Input	7.1ch		Monitor	1
	Digital OPTICAL	2			
	Digital COAXIAL	2		Analog audio REC	2
	Dock control for iPod	1		Analog Preout	1

Accessories

	AVR-588		MCS 130	
	Remote	1	Spk ear wires	5
	Batteries	2	Pln cable for subwoofer	1
	FM antenna	1	Wall mount bracket	5
	AM loop antenna	1		
	Quick setup sheet	1		

AVR-588 Specifications

Power Amplifier Section	
Rated output	*THD figures are power amp stage values.
Front	75 W +75 W (8 ohms, 20Hz - 20kHz) 110W + 110W (6 ohms, 1kHz)
Center	75 W (8 ohms, 20Hz - 20kHz) 110W (6 ohms, 1kHz)
Surround	75 W +75 W (8 ohms, 20Hz - 20kHz) 110W + 110W (6 ohms, 1kHz)
Surround Back	75 W +75 W (8 ohms, 20Hz - 20kHz) 110W + 110W (6 ohms, 1kHz)
General	
Power supply	AC 120 V, 60 Hz
Dimensions (WxHxD)	434 x 171 x 377 mm 17-3/32" x 6-47/64" x 14-27/32"
Weight	10.9 kg, 24.0 lbs

MCS 130 Specifications

LCR speakers	
Nominal Impedance	8 ohms
Dimensions (WxHxD)	125 x 351 x 103 mm 5" x 13-7/8" x 4-1/16"
Weight	2.27 kg, 5 lbs / each
Surround speaker	
Nominal Impedance	8 ohms
Dimensions (WxHxD)	140 x 214 x 102 mm 5-1/2" x 8-7/16" x 4"
Weight	1.36kg, 3 lbs / each
Subwoofer	
Power supply	AC 120 V, 60 Hz
Dimensions (WxHxD)	419 x 348 x 419 mm 16-1/2" x 13-3/4" x 16-1/2"
Weight	14.15kg, 31.2 lbs



- Design and specifications are subject to change without notice.
- Dolby and the double-D symbol are registered trademarks of Dolby Laboratories.
- DTS is a registered trademark & the DTS logos and symbol are trademarks of DTS, Inc.
- ©2007 XM Satellite Radio Inc. All rights reserved.